

## Model Information



### ■ Features

- VIA C7, 1GHz without fan, inkl. 1GB DDR2 DIMM, VGA on board
- 1 x LAN / 2 x USB 2.0
- 8 x RS232
- Compact Flash Adapter
- HDD Space S-ATA
- Power Supply AC-DC 19V
- Dimensions 256mm x 158mm x 50mm
- Audio, MIC, Line-out

[Contact Online...](#)

# EmRunner 5650

[Quick Link:](#) | [Features](#) | [More Pictures](#) | [Overview](#) | [System](#) | [Storage](#) | [Chassis](#) | [Power Requirements](#) | [Environment](#) | [Ordering Information](#) |

### ■ More Pictures



Klick on the thumbnails for the large picture ...

[>Back to top](#)

### ■ Overview

The really small and robust embedded system! Fan less, Low Power Consumption, Professional construction inside!

### ■ System

<b>CPU</b>	VIA C7 Processor (128KB cache, 1GHz)
<b>Chipset:</b>	CN700 + VT8237R
<b>Memory</b>	1GB DDR2 (1GB max.) 1x 240-pin DIMM
<b>I/O Interface Front</b>	<ul style="list-style-type: none"> <li>● HDD access/power/LAN status LEDs</li> <li>● 1x GbE LAN ports (Realtek RTL8100C Chipset)</li> <li>● 2x USB 2.0 ports</li> </ul>
<b>I/O Interface Rear</b>	<ul style="list-style-type: none"> <li>● 1x DB15 VGA port</li> <li>● 8x DB9 serial port RS232</li> <li>● 1x earphone-out</li> <li>● 1x mic-in</li> <li>● 12-24V DC power input</li> </ul>

[>Back to top](#)

### ■ Storage

<b>HDD/SSD</b>	1x 2.5" SATA HDD drive bay
<b>Flash</b>	1x internal CF socket

[>Back to top](#)

### ■ Chassis

<b>Construction</b>	Aluminium chassis with fanless design	
<b>Dimensions</b>	256 x 158 x 50 mm	<a href="#">&gt;Back to top</a>
<b>■ Power Requirements</b>		
<b>DC</b>	12V - 24V DC on-board power support	
<b>AC</b>	19V, 60W external power adapter	<a href="#">&gt;Back to top</a>
<b>■ Environment</b>		
<b>Operating Temp.</b>	0°C - 50°C	
<b>Storage Temp.</b>	-20°C – 80°C	<a href="#">&gt;Back to top</a>
<b>■ Ordering Information</b>		
<b>Part number</b>	3176 EmRunner 5650	
<b>Packing list</b>	EmRunner 5650 Embedded System (incl. CPU 1GHz, 1GB DDR RAM) Power supply Driver CD, English documentation	<a href="#">&gt;Back to top</a>

# EmRunner 5650

[>Back](#)

